Partners in Care Services™
SUPPORT | EDUCATION | PROFESSIONAL

Welch Allyn

The ABC's of Propaq LT

A	Age Ranges	Neonate: Term birth (37 weeks) through 28 days OR up to 44 weeks gestational age Pediatric: 29 days to 12 years of age Adult: 13 years of age and older
B	Battery Info	Uses a Lithium Ion battery Duration: • ECG/Resp only: ~24 hours • ECG/Resp/SpO2/BP every 15 minutes: 8hours Durations are in Standalone AND Acuity connected, continuous monitoring, and minimal display use (defined as 5 minutes display use per hour).
C	Cleaning	<u>Device</u> Wipe with a nearly-dry cloth moistened with an approved cleaning solution: • Warm water, liquid soap, Coverage®, Windex®, Ovation®, Hydrogen peroxide, Wex-cide®, T.B.Q.® After cleaning, remove excess solution with a soft cloth dampened with clean water, then dry. Do not let solution get into connector openings or crevices. Do not autoclave or immerse. <u>Accessories</u> Consult manufacturer's instructions.
D	Defaults	Create default settings using the PC Configurator Tool.
E	End Monitoring	<u>Standby/Temporary Disconnect</u> 1. Remove cables/leads from device. 2. Acknowledge equipment alert by pressing Select . 3. At Acuity, the patient's waveform tile will turn BLUE indicating 'Stand-by. 4. To resume monitoring, use good lead prep/placement to apply leads, and then plug cables back into top of device. <u>Power down/Permanent Disconnect</u> 1. Press the power button on the top right hand side of the monitor. 2. When prompted, press to select "Delete and Shut Down." 3. Remove leads from patient.